

DATA SHEET

RCP07

7 BUTTON RF WALL PLATE CONTROLLER

WHAT IS IT ?

A wireless 7 button wall mounted control panel providing 4 scenes plus off and master raise and lower.

The unit provides full scene programming.

Lithium battery powered so can be mounted anywhere without having to run cabling.

The RCP07 wireless push button wall plate controller with 4 scenes, off and master raise and lower buttons



WIRE-FREE CONTROL

The RCP07 push button wall plate controllers are designed to be mounted anywhere, be it flush mounting to UK back-boxes or simply surface mounted to any flat surface using the patress provided.

RAKOM coded radio transmission eliminates the need for any data or power cabling ensuring that the system can be installed with minimum fuss and disruption.

Flat metal cover plate accessory kits are available in a variety of standard finishes including: brushed stainless steel, mirrored stainless steel and polished brass.

Versions Available:

RCP07W - White finish

RCP07C - Charcoal finish

DATA SHEET

RCP07

7 BUTTON RF WALL PLATE CONTROLLER

TECHNICAL DATA

DIMENSIONS	86x86x14mm - flush mount 92x92x14mm - surface mount
FIXING	Flush mounting into standard UK single gang back box, minimum 12mm deep Surface mounting on standard single gang UK or European back box or direct to flat surface
INPUT SUPPLY	6V DC - 2x 3V Lithium coin cell CR2016 (remote power supply version available)
WEIGHT	100g
BATTERY LIFE	Greater than 3 years
CLIMATE RANGE	Temperature +2C to +40C Humidity +5% to 90% non condensing
STANDARDS	EMC - EN 5001-1 :1992 Immunity - EN 50082-1 :1997
COMMUNICATION	Rakom coded fm radio, 433.9MHz
MEMORY	Flash memory (non volatile)

MECHANICAL DATA

